

NAME

hyp2mat – convert hyperlynx files to octave/matlab scripts for electromagnetic simulation.

SYNOPSIS

hyp2mat [*-h*] [*-o outfile*] [*-f pdf/csxcad*] [*-n net*]... [*OPTIONS*]... [*-v*] [*infile*]

DESCRIPTION

hyp2mat 0.0.8

Converts Hyperlynx Signal–Integrity Transfer Format files to Octave/matlab scripts.

OPTIONS

-h, --help

Print help and exit

-V, --version

Print version and exit

-o, --output=*filename*

Output file. (default='–')

-f, --output-format=*ENUM*

Output file format. (possible values="csxcad", "pdf" default='pdf')

Processing options:

-n, --net=*STRING*

Import net. Repeat to import several nets. Default is importing all nets.

-l, --layer=*STRING*

Import layer. Repeat to import several layers. Default is importing all layers.

-e, --epsilon_r=*DOUBLE*

Set dielectric epsilon r.

-x, --xmin=*DOUBLE*

Crop pcb. Set lower bound of x coordinate.

-X, --xmax=*DOUBLE*

Crop pcb. Set upper bound of x coordinate.

-y, --ymin=*DOUBLE*

Crop pcb. Set lower bound of y coordinate.

-Y, --ymax=*DOUBLE*

Crop pcb. Set upper bound of y coordinate.

-z, --zmin=*DOUBLE*

Crop pcb. Set lower bound of z coordinate.

-Z, --zmax=*DOUBLE*

Crop pcb. Set upper bound of z coordinate.

-g, --grid=*DOUBLE*

Set output grid size. (default='10e–6')

-p, --arc-precision=*DOUBLE*

Set maximum difference between perfect arc and polygonal approximation. (default='0')

-c, --clearance=*DOUBLE*

Set default trace–to–plane clearance. (default='0')

PDF output options:

--hue=*DOUBLE*

Set PDF color hue. Range 0.0 to 1.0 (default='0')

- saturation=DOUBLE**
Set PDF color saturation. Range 0.0 to 1.0 (default='0.6')
- brightness=DOUBLE**
Set PDF color brightness. Range 0.0 to 1.0 (default='0.9')

Debugging options:

- r, --raw**
Raw output. Do not join adjacent or overlapping copper. Do not invert planes. (default=off)
- d, --debug**
Increase debugging level. Repeat for more detailed debugging.
- v, --verbose**
Print board summary.

All lengths are in meters.

Hyperlynx input files conventionally end in **.hyp** .

hyp2mat reads input from file *infile*. If no input file is specified input is read from standard in.

If no output file is specified output is to standard out.

If a syntax error occurs during conversion, error recovery is attempted. *hyp2mat* exits with zero status if conversion was successful and non-zero if not.

The **--verbose** option can be used to list board dimensions.

If only a small region of the board needs to be simulated the **--xmin --xmax --ymin --ymax --zmin** and **--zmax** options can be used to crop the board to a smaller region.

If not all layers of the board need to be simulated, the **--layers** option may be used to specify layers of interest.

If not all nets of the board need to be simulated, the **--nets** option may be used to specify nets of interest. The option **--net=?** lists all available nets.

Circles and arcs are approximated by polygons. By default a circle is approximated by an octagon. If higher accuracy is needed, set **--arc-precision** to the desired precision. This will increase the number of line segments used to draw circular, oval and oblong pads, amongst others.

Typical use of *hyp2mat* is with simulation packages such as OpenEMS.

FILES

/usr/share/hyp2mat/matlab/
Supporting matlab routines for OpenEMS.

/usr/share/hyp2mat/eagle/
Examples and tutorial.

EXAMPLES

Convert pcb.hyp to pdf:
`hyp2mat -o pcb.pdf pcb.hyp`

Examine original Hyperlynx file:
`hyp2mat -o pcb.pdf --raw pcb.hyp`

Draw arcs with an accuracy of 10 mil or better:

```
hyp2mat -o pcb.pdf --arc-precision 0.000254 pcb.hyp
```

NOTES

Board outlines and copper polygons should not be self-intersecting.

Common causes of syntax errors are unquoted strings, and unassigned component values.

Unquoted strings

Error: *syntax error, unexpected STRING at 'Logo'*

Source:

```
(? REF=My Logo BOT1 L=Bottom_Layer)
```

Cause: An unquoted string contains a space (' ').

Solution:

Edit the .hyp file and put the string between double quotes:

```
(? REF="My Logo BOT1" L=Bottom_Layer)
```

Unassigned component values

Error: *syntax error, unexpected L, expecting FLOAT or STRING at 'L'*

Source:

```
(R REF="R1" VAL= L="Top")
```

Cause: Component has not been assigned a value (VAL=).

Solution:

Edit the .hyp file and assign a value to resistor R1:

```
(R REF="R1" VAL=0 L="Top")
```

or assign the resistor a value in the schematics editor and re-export to HyperLynx.

AUTHOR

Koen De Vleeschauwer, <http://www.kdvelectronics.eu>

SEE ALSO

octave(1)

OpenEMS, a free and open-source electromagnetic field solver using the FDTD method.